

Item number: 1.13.0142.01002

The Ixxat FRC-EP170 CANonly is a compact solution for automotive uses, focusing on CAN-based operations. It features four CAN channels, one of which is CAN low-speed capable, including LIN and Digital in/out functionalities. This makes it an ideal solution for logging, gateway, and residual bus simulation applications. Configuration is easily done with the Ixxat Advanced Configuration Tool (ACT).



Configurable automotive platform (4x CAN)

Features and benefits

Go-to solution for demanding network requirements Enables easy integration of multiple bus systems into a single, compact device. This is essential for e-mobility projects and complex industrial applications.



Multi-connectivity with various interfaces

Additional interfaces included: 1 x LIN, 1 x Ethernet (10/100 Base-T), 4 x Digital in/out (A/D), USB 2.0 device and host and a SDHC slot. Further extension options are available.

Embedded platform with own processing power

All applications run on the device, a PC is only needed for configuration or stimulation/visualization of data, as the actual intelligence is outsourced to the embedded platform.

Support for Linux and QNX

Using the free ECI driver package, the hardware can be easily integrated into Linux-based environments as well as into applications under the QNX real-time operating system. 32- and 64-bit ARM (Raspberry Pi) and Intel X86 platforms are supported.

Extensive CAN connectivity

The FRC-EP170 CANonly features four CAN channels, thereof one CAN low-speed capable, catering extensive connectivity for a wide range of automotive applications.

Improved data management for efficient engineering \bigtriangledown

Streamlines data management and protocol handling, optimized for automotive testing, logging and gateway operations. Ensuring easy integration and reliable performance.

Quick and easy configuration through ACT support

The FRC-EP series is supported by the Ixxat ACT (Advanced Configuration Tool), a Windows-based tool to easily configure the device via drag and drop. Most use cases can be solved by using ACT Freeware.





General	
Net Width (mm)	113
Net Height (mm)	142
Net Depth (mm)	40
Net Weight (g)	920
Packed Weight (g)	920
Operating Temperature °C Min	-40
Operating Temperature °C Max	80
Storage Temperature °C Min	-40
Storage Temperature °C Max	85
Relative Humidity	10 to 95 %, non-condensing
Current Consumption Type Value at Vcc Nom (mA)	320 mA (12 V DC)
Input Voltage (V)	6 V to 36 V DC
Power Connector	3-pole
Configuration	The Ixxat FRC-EP170 is a Linux platform that is able to work standalone without any connected PC. For the standalone function a configuration is needed, that can be created and downloaded to the device via the PC based Ixxat Automotive Configuration Tool (ACT) and an USB connection.
Content of Delivery	FRC-EP170 device, user manual, power supply cable (2 m, 3-pin Binder socket to 3 x 4 mm banana plugs), USB 2.0 cable (2 m, Type A to Mini Type B), runtime licences for Gateway and RBS, available as download: Advanced Configuration Tool (ACT)
Mounting	Panel mount
Housing Materials	Aluminium
Packaging Material	Cardboard

Identification and Status

Product ID

1.13.0142.01002





Identification and Status		
Country of Origin	Germany	
HS Code	8517620000	
Dual Usage	No	
Export Control Classification Number (ECCN)	EAR99	
Physical Features		
Connectors / Input / Output	1 x RJ45 connector (Ethernet), 1 x USB type B port, 1 x USB type A port, 1 x SD card slot, 1 x 7-pin Binder female panel mount connector (remote/debug), 1 x 3-pin Binder male panel mount connector (power), 1 x D-Sub HD15 male connector, 1 x D-Sub HD15 female connector, 1 x RP-SMA female connector (WiFi/antenna)	
Contains Battery	No	
CAN Features		
CAN Mode	CAN high-speed (ISO 11898-2), CAN low-speed (ISO 11898-3)	
CAN Transceiver	TI SN65HVD251	
CAN FD Features		
CAN FD Transceiver	TCAN334GDCN	
LIN Features		
LIN Transceiver	TJA1020	
Certifications and Standards		
Protection Class IP	IP42	
ETIM Classification	EC001604	
CE	Yes	
TELEC	No	
WEEE Category	IT and telecommunications equipment	



Use Case



