

Panasonic ECOi and PACi systems to Home Automation Interface

Item number: INWMPPAN001R000

The Panasonic gateway allows complete and natural integration of Panasonic ECOi and PACi Air Conditioner units into IP-based Home Automation Systems. The device connects to the indoor unit through a direct cable and to the Home Automation interface via Wi-Fi. A wired remote controller can also be connected.

Features and benefits

Intuitive web interface for Wi-Fi configuration

Wi-Fi configuration is carried out quickly and easily through an intuitive web interface.

Quick and easy installation

The installation process takes only seconds; just plug in the interface and configure the Wi-Fi.

AC unit control by remote and Home Automation

The remote controller and the Home Automation system can control the AC unit simultaneously.

Driver compatibility

A wide range of compatible drivers is available on the Intesis webpage.

Panasonic to Home Automation - 1 indoor unit

2,4 GHz 802.11 b/g/n Wi-Fi networks supported

Different Wi-Fi standards are supported, being compatible with 2,4 GHz 802.11 b/g/n Wi-Fi networks.

No external power required (exceptions may apply)

An external power supply may be required In some cases. Requirements are shown in the documentation.



Thanks to our open ASCII protocol, integration is possible with any IP Home Automation System.



Panasonic ECOi and PACi systems to Home Automation Interface

| General | |
|------------------------------|--|
| Net Width (mm) | 70 |
| Net Height (mm) | 100 |
| Net Depth (mm) | 28 |
| Net Weight (g) | 81 |
| Packed Width (mm) | 120 |
| Packed Height (mm) | 80 |
| Packed Depth (mm) | 100 |
| Packed Weight (g) | 178 |
| Operating Temperature °C Min | 0 |
| Operating Temperature °C Max | 60 |
| Input Voltage (V) | From the AC unit. |
| Power Connector | Other |
| Capacity | 1 indoor unit. |
| Installation Conditions | This gateway is designed to be mounted inside an enclosure. If the unit is mounted outside an enclosure, precautions should always be taken to prevent electrostatic discharge to the unit. When working inside an enclosure (e.g., making adjustments, setting switches, etc.), typical anti-static precautions should always be followed before touching the unit. |
| Content of Delivery | Intesis Gateway, Installation Manual. |
| Mounting | Wall mount |
| Housing Materials | Plastic |
| Warranty (years) | 3 years |
| Packaging Material | Cardboard |



Panasonic ECOi and PACi systems to Home Automation Interface

| Identification and Status | |
|--|-------------------------------------|
| Product ID | INWMPPAN001R000 |
| Country of Origin | Spain |
| HS Code | 8517620000 |
| Export Control Classification Number (ECCN) | EAR99 |
| Supply Risk Factor ERP | Volume not defined yet |
| Purchasing Multiple ERP | 1 |
| Certifications and Standards | |
| ETIM Classification | EC001604 |
| WEEE Category | IT and telecommunications equipment |



Use Case



Integration of Panasonic ECOi & PACi systems into a Home Automation installation.

