

Anybus CompactCom

Connector Board - DeviceNet

Item number: AB6664-B

Used together with the CompactCom Brick to get quick and easy access to network connectors.



Features and benefits

Easy mounting

Incorporates a male strip connector - pluggable and solderable.

Modular

Mix and match CompactCom Bricks and connector boards to give your host application access to different networks.

Robust

Safe and secure mounting of the brick interface to the host PCB design.

Compatible with Starter Kit

Used together with the Anybus CompactCom Starter Kit (Brick version) to get access to the right network connectors.



Anybus CompactCom Connector Board -DeviceNet



| General | |
|------------------------------|--|
| Net Width (mm) | 40 |
| Net Height (mm) | 16 |
| Net Depth (mm) | 35 |
| Net Weight (g) | 10 |
| Packed Width (mm) | 8 |
| Packed Height (mm) | 3 |
| Packed Depth (mm) | 7 |
| Packed Weight (g) | 30 |
| Operating Temperature °C Min | -40 |
| Operating Temperature °C Max | 85 |
| Storage Temperature °C Min | -40 |
| Storage Temperature °C Max | 85 |
| Isolation | Galvanic Isolation |
| Content of Delivery | Connector board |
| Not Included (in delivery) | Female strip connector, stand-off spacer |
| Mounting | PCB mounting via a customized CompactFlash connector |
| Warranty (years) | 1 year |
| Identification and Status | |

| Product ID | AB6664-B |
|-------------------|----------|
| Country of Origin | Sweden |



Anybus CompactCom Connector Board - DeviceNet



| Identification and Status | |
|---|---------------------|
| HS Code | 8517620000 |
| Dual Usage | No |
| Export Control Classification Number (ECCN) | EAR99 |
| Physical Features | |
| Connectors / Input / Output | 1x 5-pin 5.08 MSTBA |
| Contains Battery | No |





Use Case



